

Goal Zero - Power banks Sherpa 100 AC and PD GEN4

SHERPA 100AC GEN4

Sleek and powerful, the Sherpa 100AC is your goto source for versatile power while on the move. Airline approved and travel ready, the 94.72Wh power bank is equipped with innovative features like wireless charging, high-speed Power Delivery, and a variety of ports to power phones, tablets, DSLR cameras, and laptops—including powerhungry MacBooks.

Integrated 100W AC

Take the outlet with you, on the plane or in the wild, for serious power anywhere you need it.
Perfect for keeping cameras and laptops charged.

Qi Wireless Charging + 2.4A USB

No matter the phone, there's a wicked fast, convenient charging solution designed for you. Charge your iPhone and use your headphones at the same time on long flights using Qi wireless charging.

Interactive OLED Display

Check power in and power out, get detailed port information, and even set roles for ports.

Whats in the box

Apart from the Sherpa 100AC, a 1m USB-C cable is included.

SHERPA 100PD GEN4

The new and airline-approved Sherpa 100PD features 60% faster USB-C charging with 60W in and 100W out, and best-in-class 15W wireless charging. Charge your phones, tablets, and laptops with 95 watt-hours of power while working remotely, and rest easy knowing your Sherpa 100PD is built to last through your travels.

Integrated 100W

Power goes in at 60W and out at 100W via USB-C for 60% faster device charging than previous models, making it easy to keep your essentials charged.

Wireless Charging

Best-in-class* up to 15W wireless charging that's 3x faster for keeping your phone charged up while working on the go.

*50-100Wh power banks with wireless charging capabilities.

Color Display

Color LCD display keeps it simple. It's easy to operate and makes viewing critical power stats uncomplicated.

Whats in the box

Apart from the Sherpa 100PD, a 1m USB-C cable is included.







Contact Danimex for more information or visit **www.danimex.com/goal-zero**

DMX-2023-01



Technical Specifications

SHERPA 100AC GEN4	
Charge times	 USB-C Wall Charger (65W): 2 hrs Nomad 20: 7.5-15 hrs Nomad 50: 3-6 hrs Boulder 50: 3-6 hrs
Ports	 Wireless (output): 15W max (2) USB-A: 5V, up to 2.4A (12W max), regulated USB-C PD ports (input/output): 5V, 9V, 12V, 15V, 20V up to 5A (100W max), regulated AC inverter (output): 110V, up to 0.9A (100W max), 60Hz, modified sine wave Solar Charging port (input, 8mm): 8-22V (60W max)
Battery details	 Cell chemistry: Li-ion Pack Capacity: 94.7Wh (14.8V, 6400mAh) Single Cell Equivalent Capacity: 25600mAh @ 3.7V Shelf-life: Charge every 3-6 months Management system: Charging and low-battery protection built-in
General	 Simultaneous Recharge & Discharge: Yes Product SKU: 22210 Weight: 2.0 lbs Dimensions: 7.69 x 5.51 x 1.02 in (19.53 x 13.99 x 2.59 cm) Operating usage temp: 32-104F (0-40C) Certifications: CE, FCC, RoHS, UKCA Warranty: 2 years
What can the sherpa 100AC power?	The Sherpa 100AC is great for all your laptops, tablets, or multiple USB powered devices. POV Camera 19 Recharges (5Wh) Smartphone 8 Recharges (12Wh) up to Tablet 3 Recharges (30Wh) up to Laptop 2 Recharges (50Wh)

SHERPA 100PD GEN4	
Charge times	 USB-C Wall Charger (65W): 2 hrs Nomad 20: 7.5-15 hrs Nomad 50: 3-6 hrs
Ports	 Wireless (output): 15W max (2) USB-A: 5V, up to 2.4A (12W max), regulated USB-C PD port (input): 5V, 9V, 12V, 15V, 20V up to 3A (60W max), regulated USB-C PD port (output): 5V, 9V, 12V, 15V, 20V up to 5A (100W max), regulated
Battery details	 Cell chemistry: Li-ion Pack Capacity: 94.7Wh (14.8V, 6400mAh) Single Cell Equivalent Capacity: 25600mAh @ 3.7V Shelf-life: Charge every 3-6 months Management system: Charging and low-battery protection built-in
General	 Simultaneous Recharge & Discharge: Yes Product SKU: 22220 Weight: 1.5 lbs Dimensions: 7.69 x 3.81 x 1.02 in (19.53 x 9.68 x 2.59 cm) Operating usage temp: 32-104F (0-40C) Certifications: CE, FCC, RoHS, UKCA Warranty: 2 years
What can the sherpa 100PD power?	The Sherpa 100PD is great for all your laptops, tablets, or multiple USB powered devices. POV Camera 19 Recharges (5Wh) Smartphone 8 Recharges (12Wh) up to Tablet 3 Recharges (30Wh) up to Laptop 2 Recharges (50Wh)









